

THE CAT® INV4000 E

PORTABLE INVERTER GENERATOR

Running Power	3500 Watts
Starting Power	4000 Watts
AC Output	120 V @ 60 Hz
Run Time @ 50% Load	7 hrs
Fuel Tank Nominal Capacity	2 gal / 7.5 L
Starting Method	Pull or Electric
Engine Displacement	212 cc
Engine Type	OHV
Engine Speed	Variable RPM
Fuel Type	87 octane or greater unleaded gasoline* (no more than 10% ethanol)
Recommended Oil	SAE30 or 10W-30
Lubrication Method	Splash
Power Outlets	1x 5-20R GFCI Duplex 1x TT-30R (RV Outlet) 1x 5V 2.1A USB 1x 5V 1.0A USB 1x DC 12V 8.3A
Battery Type	Litium Ion
Voltage Regulation	Inverter Type
Fuel Gauge	LCD Display
Warranty	3-Year**
USB	1x 1.0A 5V and 1x 2.1A 5V

* Fuel stabilizer should also be used for storage

**2-year limited, 3-year limited when registered within 30 days

For more information on our current generator lineup, visit: cat.com/portablepower

CARBON MONOXIDE SHUTDOWN

to keep you and your family safe

ENGINE SMART CONTROL (ESC)

automatically adjusts power to your exact needs – no more, no less

INTUITIVE START/STOP SWITCH

with integrated choke

DUAL USB PORTS

to charge phones, tablets and laptops

ELECTRIC START WITH LITHIUM ION BATTERY

for easy start and stop

DOUBLE THE POWER

by connecting a second INV4000 E

CONTROL PANEL WITH LCD DISPLAY

shows power output, fuel level, voltage, frequency, running hours and total hours

NO MESS

unique no-drip oil fill/drain design

SERVICE WITH EASY ACCESS

to air filter and fuel drain

AUTOMATIC LOW-OIL SHUTDOWN PROTECTION

provides peace of mind for long-lasting operation

